


P1PE GENERATOR

# P10000LE

User Manual

**FOR YOUR SAFETY**  
You must read and understand  
this manual before use.  
Keep this manual for future  
reference.



# Table of Contents

<b>Fore ward.</b> .....	<b>3</b>
<b>Safety Precautions.</b> .....	<b>4</b>
<b>Safety Specification</b> .....	<b>5</b>
<b>Safety Regulation</b> .....	<b>6</b>
<b>Warning Labels</b> .....	<b>7</b>
<b>Product Specifications</b> .....	<b>8</b>
<b>Component Identification</b> .....	<b>9</b>
<b>Features.</b> .....	<b>10</b>
<b>Operating Guide</b> .....	<b>11</b>
<b>Operating</b> .....	<b>12</b>
<b>Power Management</b> .....	<b>14</b>
<b>Maintenance</b> .....	<b>15</b>
<b>Trouble Shooting Guide</b> .....	<b>18</b>
<b>Recycling &amp; Product Disposal</b> .....	<b>19</b>
<b>Declaration of Conformity</b> .....	<b>20</b>
<b>Contact Details</b> .....	<b>21</b>

# Foreward

Thank you for buying this P1PE generator unit. This product is a household generator which produces electrical power by means of an engine driving a alternator, and is used in situations where electricity supply is interrupted or as a primary source of power supply where power is unavailable.


## Please Read Instructions Carefully

If you DO NOT understand any part of this manual, please contact your dealer for any startup, operation and maintenance concerns. It is recommended that you read this manual to understand all requirements and operating steps of this generator before you use it. Keep this manual in good condition for reference in case of emergency in the future. If you lend or sell the generator unit, make sure to supply this manual. The generator can be operated in a safe, effective and reliable way only when it is kept, operated and maintained properly. Before operating or carrying out maintenance of the generator unit, the operator will:

- Know well and strictly observe local laws and regulations.
- Read the manual carefully and observe all safety warnings in this manual and on the generator.
- Instruct others on the proper use of this generator and be sure they are familiar with all safety warnings in this manual before use.

It is impossible for manufacturers to predict all possible dangerous situations, therefore, warnings in this manual and labels on the generator unit may not identify all hazards. If no special suggestions are raised with respect to the operation procedures, working procedures or operating skills, use this generator in a manner which guarantees personal safety. In addition, make sure no damage to the generator unit is caused by the operating procedures, working methods or operating skills.

Information contained here is based on the machine in production at time of publication. P1 Power Equipment reserve the right to change any parts described in the text without notice in advance.

Please read carefully the ALL safetywarnings in the instructions and on the decals of the generator unit, with symbol  in front. Details are shown as follows:




**Danger:** You may cause yourself serious injury if you do not follow these warning labels.




**Warning:** You may suffer serious harm by ignoring this label


# Safety Precautions




**⚠** Danger: Use outdoors only, exhaust gas released from the equipment contains Carbon Monoxide (CO), which cannot be seen or smelt. Excessive inhalation of CO may cause a loss of consciousness and may claim life in extreme circumstances.




**⚠** Danger: Do not connect the generator unit with mains supply or other power sources, use it alone.




**⚠** Warning: Do not use this generator if exposed to rain or if wet, and store in an enclosed area when not in use.



**⚠** Warning: Properly ground the generator and verify grounding is in place before each use.



**⚠** Warning: Keep the generator clean, remove any petrol or oil spills on or around the generator.



**⚠** Warning: DO NOT touch HOT surface or you may be injured or suffer burns.

# Safety Specification



## **Danger: Electrocutation hazard - Electricity can cause DEATH or SERIOUS INJURY**

- DO NOT use bare wire to connect power supply to electrical equipment, use a plug that meets local regulations.
- During generator operation, do not touch exposed wires.
- During generator operation, keep children a safe distance from the generator unit.
- DO NOT use the generator unless it is fully assembled as instructed in this manual.
- Properly ground the generator and verify grounding is in place before each use. Grounding regulations vary by location, consult a qualified electrician for verification.
- Accessories including cables and plug must not be defective. Electric shock prevention hinges on the breaker. If you renew the breaker use a breaker with the same rating and performance features, contact your local authorized service agent.



## **Danger: Fuel used by the generator is combustible, as this equipment generates high temperature, this causes a fire risk in some circumstances , such as refueling.**

- It is strictly prohibited to add fuel while the generator is operating;
- When adding fuel, keep far away from any ignition source, and NO smoking;
- When adding fuel, pay attention not to spill fuel on the equipment, if fuel is spilt ; clean it immediately, and only start it up when the spilt fuel has evaporated completely;
- During operation, be sure there are no combustibles within a 2m range.
- In case of long-term nonuse, make sure you use a fuel stabilizer or empty the fuel tank and bowl.



## **Caution: This equipment contains high speed revolving parts, which may cause injury.**

- During generator operation, avoid coming into contact with any revolving parts.
- During generator operation, observe surroundings, make sure there is no risk to the generator, other people and nearby equipment.
- During generator operation, do not lift or re-position. Turn the generator off ensuring it has come to a complete stop.

## **Attention: operating requirements**







- Do not place weight on the equipment.
- The wheel is adopted for convenience of equipment moving, do not use it in long distance, otherwise it will be damaged.
- Do not exceed rating power of the equipment in operation; otherwise, its service life will be shortened. Power of common household appliances is shown on Page 14 in details.
- Maintain the equipment based on requirements so as to prolong its service life, refer to Page 15-17 for details.
- Operate and store the generator in a dust free area this prevents dust entering inside of the equipment which reduces its working life.






# Safety Regulations

There is the warning decal on the machine to remind you of the safety regulations.

**⚠ WARNING**

 <p>You <b>WILL</b> be <b>KILLED</b> or <b>SERIOUSLY HURT</b> if you do not follow the operator's manual instructions.</p>	 <p>Generator is a potential source of electric shock. Do not expose to moisture, rain, or snow. Do not operate with wet hands or feet.</p>	 <p>Failure to properly ground generator can result in electrocution, especially if the generator is equipped with a wheel kit.</p>
 <p>Risk of fire. Do not add fuel while the product is operating.</p>	 <p>Exhaust contains poisonous carbon monoxide gas that can cause unconsciousness or <b>DEATH</b>. Operate in well ventilated, outdoor areas away from open windows or doors.</p>	 <p>Do not expose to rain or use in damp locations.</p>






**BURN RISK**



**CARBON MONOXIDE**
















**SAFE DISTANCE**



**DON'T TOUCH**

# Warning Labels

Some of following symbols are used in the machine or the manual. To understand their meanings will make it easy and safe for you in operation.



Symbol	Name	Meaning
V	Volt	Voltage Unit
A	Ampere	Current Unit
Hz	Hertz	Frequency Unit (1Hz=60 r/min)
W	Watt	Power Unit
RPM	Revolution Per Minute	Speed Unit
PF	Power Factor	Generator Efficiency
G1	Performance Rate	Performance Rate
	Read Instructions	Please read instructions carefully before using.
	Safety Warning	Risk of harm in the case of not following instructions.
	Electrocution Risk	Indicate that there is an electrified body here, pay attention to safety.
	Electric Shock	This is an electric device, failure to observe the indication may result in an electric shock.
	Electricity, Do Not Touch	The device produces electricity, do not touch during operation.
	Toxic Gas	Exhaust gas from this generator contains Carbon Monoxide (CO), a colorless & odorless gas. Excessive exposure to CO may cause loss consciousness and may lead to death in extreme circumstances.
	Fire	High temperature generated from operation may cause fire, so operate it with caution.
	Explosion	If the fuel tank is exposed to high temperature or open fire it may explode.
	Burns	Some parts will generate high temperature in operation, this will burn the skin.
	Grounding	Consult an electrician to determine grounding. Make sure the generator is safely grounded before operation.
	Water Exposure	Do not use a plug or electric device on rainy days or if they are wet.
	Engine Oil	Engine oil symbol and the specification is based on Page 9.
	fuel	Fuel symbol.

## Product Specifications

Model	P10000LE
Frequency	50hZ
Voltage	230V – 240V
Power Factor	1.0
Rated Power	7500W
Max Power	7900W
Fuel Tank Capacity	25L
Engine Type	4 Stroke Air Cooled Single Cylinder OHV
Oil Capacity	1.1L
Starting Method	Electric / Recoil
Displacement	457cc



# Component Identification



# Features

## **KNOW YOUR GENERATOR**

The safe use of this generator requires an understanding of the information provided in this operator's manual as well as a knowledge of the project you are attempting. Before use of this generator, familiarize yourself with all operating features and safety rules.

## **AC CIRCUIT BREAKER**

The circuit breakers are provided to protect the generator against electrical overload. The circuit breaker may be reset by pressing the circuit breaker reset button.

## **AIR FILTER**

The air filter helps to limit the amount of dirt and dust drawn into the unit during operation.

## **CHOKE LEVER**

The choke lever is used when starting the engine.

## **FUEL TANK**

The fuel tank has a capacity of 25 litres.

## **FUEL VALVE**

Fuel flow from the fuel tank to the engine is turned on and off using the fuel valve. Turn fuel off after use.

## **GROUND TERMINAL**

The ground terminal is used to assist in properly grounding the generator to help protect against electrical shock. Consult with a qualified local electrician for grounding requirements in your area.

## **LOW OIL SHUT DOWN PROTECTOR**

The low oil sensor causes the engine to stop if the level of oil in the crankcase is insufficient.

## **OIL CAP/DIPSTICK**

Remove the oil fill cap to check and add oil to the generator when necessary.

## **OIL DRAIN PLUG**



When changing the engine oil, unscrew and remove the oil drain plug to allow old engine oil to be drained.

## **RECOIL STARTER GRIP**

The recoil starter grip is used to start the generator's engine manually.

# Operating Guide


The operational steps are pasted above the fuel tank, . please operate as per the instructions.



## Fill fuel oil



Do Not exceed this level



Open the fuel fill cap and fill with fresh Unleaded petrol.

The fuel level position will be displayed on the indicator opposite the fuel cap. When filling the tank the maximum fuel position shall not exceed the inner strainer of the Fuel tank as indicated above.




**Warning:** keep away from any possible ignition source when filling petrol; do not fill the fuel tank while the generator is in operation.

## Unit grounding

Shift the machine outdoors, use the grounding terminal connection wire to ground to earth. One end of the wire is pressed below the butterfly nut on the unit, screw it up tightly, and the other end is connected with the metal rod that is inserted into the ground.

## Pre-operational

### Add engine oil



Unscrew the oil dip stick, add engine oil SAE30 or 15w40 (oil requirements may vary if operating in extreme temperatures, refer above table). Fill the oil to the top of the thread (indicated as "Correct Oil Level" above).

If oil is spilt wipe off machine to avoid fire hazard and from the ground to avoid slipping.


## Connect electric battery (electrical starting only)

Connect the battery, red for positive terminal and green for the negative terminal and make sure you tighten the nuts. Pay attention and avoid contact between positive and negative terminal to eliminate the chance of short circuit. Make sure you place the rubber protective covers over the terminals.


# Operation

## Starting the Engine


1. Unplug all loads from the generator.




2. Turn the Fuel valve to the ON position.




3. Move the choke lever to the CHOKE position.  
NOTE: If engine has been operating and is being restarted leave the choke lever in the RUN position.




4. Turn the switch on the control panel to ON.
  - a. The generator unit is electric.




start and can be started by turning the switch around to the START position. In order to extend the service life of the battery, do not turn the switch for more than 3 seconds and the interval between two attempts should be at least 10 seconds apart.



- b. For the manual start generator by pulling the recoil starting grip until the engine runs. NOTE: Do not allow the grip to snap back after starting; return it gently to its original place. Allow the engine to run for 10-20 seconds, then move the choke lever to the RUN position.



5. To operate electrical equipment, turn the circuit breaker ON. Please note that when using several appliances at the same time, do not add the next one unless the generator and other items are running normally. The total power of the loads should not exceed the rated power of the unit.







# Operation

## Stopping the Engine


1. Remove any load from the generator.



2. Turn the engine switch to the OFF position.



3. Turn the fuel valve to the OFF position.




### To stop the unit quickly in an emergency:


Turn the engine switch to the OFF position.

#### Warning:

The surface temperature of the generator unit are still high after shutdown, and it should not be moved or touched before cooling down to avoid the possibility of burns.



The unit should be stored in a clean and dry place and should be protected from rain and high temperature. Covering the unit is recommended to avoid excessive exposure to moisture and dust.



If the generator is not used regularly remove the fuel via the drainage bolt of the carburetor and drain the fuel tank. Then tighten the oil drainage bolt again. If a quality fuel stabilizer is used then this procedure can be ignored.

## Power Management

	Electric equipment	Rated power(W)	Starting power(W)
Household Appliances	Flat panel television 27"	500	800
	Energy saving lamp	5~50	5~50
	Electric cooker	1000	1000
	Computer	800	800
	DVD	100	100
	Refrigerator	800	1600
	Washing machine	300	600
	Electric fan	50	100
	Air-conditioner 2HP	1500	3000
Tools	Electric welder	2500	5000
	Electric hammer	1000	1500
	Water pump	800	1200

The starting wattage of some appliances can be higher than the operating watts. Please read the labels of the electric equipment for reference. The total power of the loads should not exceed the rated power of the generator.



# Maintenance

Regular maintenance is the best guarantee of safe, economical and fault-free operation, and can also contribute to environmental protection.


Maintenance schedule is as follows- Please carry out the recommended maintenance at the earlier of the stated hours or elapsed time.

Schedule for regular maintenance		Per use	Every 20 hours or in the first month of initial use (3)	Every 50 hours or every 3 months (3)	Every 100 hours or every 6 months (3)	Every 300 hours or every year (3)
Engine oil	Inspect the oil level	○				
	Replace		○		○	
Air filter	Inspect	○				
	Clean			○ (1)		
Fuel strainer bowl	Clean				○	
Spark plug	Clean				○	Replace
Valve clearance	Readjust					○ (2)
Cylinder head	Wash	Every 300 hours (2)				
Fuel tank and strainer	Wash	Every 2 years (2)				
Oil tube	Replace	Every 2 years (2)				

(1) Maintenance should be conducted more frequently if the unit is used in dusty conditions.


(2) Maintenance should be conducted by an authorized Stanley generator dealer (to find one see [tpeaustralia.com.au/dealers](http://tpeaustralia.com.au/dealers)).

## Replace the engine oil



# Maintenance


## Clean the air filter



The air cleaner system uses a foam element that can be washed and reused.

1. Open the cover with the lock nut and remove the foam air filter element.
2. Wash the foam element in liquid detergent and water, then rinse in clean water and squeeze dry in a clean cloth.
3. Saturate the foam filter with clean engine oil, remove excess by squeezing into a dry clean cloth.
4. Refit the air filter and air filter cover.

## Clean the fuel bowl





1. Close the fuel valve and remove the sediment bowl. Take out the O-type seal ring and strainer.
2. Clean the sediment bowl, O-type seal ring and strainer with incombustible or high-flash solvent.
3. Reinstall the O-type seal ring and strainer, and tighten the sediment bowl.
4. Open the fuel valve and inspect for leakage.

# Maintenance

## Clean the spark plug

Recommended spark plug models: NGK: BPR7ES. Champion RN7YC.


Spark plug socket spanner



- 1 Remove the spark plug cap.
- 2 Clean the spark plug base.
- 3 Remove the spark plug with the spark plug socket spanner.
- 4 Inspect the spark plug insulator visually for damage. If it is damaged, replace a new one.
- 5 Measure the spark plug clearance with a feeler gauge. The clearance should be kept between 0.70 and 0.80mm.
- 6 Inspect if the washer of the spark plug is in good condition.
- 7 Reinstall the spark plug and tighten it with the spark plug socket spanner. Press down the washer of the spark plug and place the spark plug cap.

## Valve clearance (should be conducted by a professional person)

Feeler gauge



Remove the cylinder cover and measure the valve clearance with the feeler gauge. The clearances are 0.1mm for the inlet valve and 0.15mm for the outlet valve.

# Trouble Shooting

Fault	Cause	Action
The unit can not start	No fuel	Fill the oil tank with petrol
	The Fuel valve is not turned on	Turn the fuel valve to ON
	The Fuel valve is blocked	Clean the fuel bowl (refer to page 16)
	No engine oil or the engine oil level is low	Add oil
	The engine switch is turned off	Turn the switch to the “on” position
	The spark plug fails	Clean or replace the spark plug (refer to page 17)
There is no power output	The circuit breaker is in the off position	Turn the circuit breaker to the “on” position
	The plug is poorly contacted	Remove and refit the plug.
The unit shudders during operation	The choke lever position is incorrect	Move the choke lever to the “open” position during operation
The unit emits white smoke	The temperature of the engine is too high, maybe overloaded	Let the engine run without load for more than 10 minutes
	The fuel is contaminated	Use fresh clean fuel
The unit emits black smoke	The air filter is dirty	Clean the filter element of the air filter
	The load is too heavy	Reduce load to the rated limit
The unit emits blue smoke	The engine oil is overfilled	Drain oil to correct level
	The engine oil type is incorrect	Choose appropriate engine oil model (refer to page 11)
The power decreases	The spark plug fails	Clean or replace the spark plug (refer to page 17)
	The valve clearance are out of adjustment	Adjust the valve clearance (refer to page 17)


The environmental condition required to operate the generator:

- Suitable temperature: -15°C-40°C.
- Suitable humidity: lower than 95%.
- Suitable altitude: under 1,000 meters (The power load should be reduced where the generator is used at altitudes greater than 1000 meters.)

**The generator unit can only be loaded to the rated power under the specified environment conditions. If the environment conditions are inconsistent with the above standards, or if the cooling conditions of the engine and generator unit are poor; for example, when operating in enclosed areas, it is necessary to reduce the power load. It is also necessary to reduce the power load when the temperature, altitude or relative humidity exceed the standards.**

**If the generator does not work properly in optimal conditions, please take to the nearby dealer or after-sales service center for inspection.**

## Recycling & Product Disposal



1. We do not offer a takeback scheme for the recovery of Waste Electrical Electronic Equipment (WEEE) and batteries.  
Instead the responsibility to dispose of WEEE and or Batteries is passed onto you by us.  
So when it becomes necessary to dispose of your machine, you must take it to your local Civic Amenity Site.  
For further information please contact your local Authority for disposal advice.
  2. You **MUST** make sure that all unused oil and fuel is disposed of correctly either beforehand or at your local Civic Amenity Site.  
Under NO circumstances must any fuel or oil be put down any drains.
  3. Certain products contain WEEE waste which should not be disposed of in your domestic waste.
  4. You **MUST** recycle WEEE in accordance with your local authority or recycling centre.
  5. Certain products contain batteries which should not be disposed of in your domestic waste.
  6. You **MUST** recycle batteries in accordance with your local authority or recycling centre.
  7. Unwanted packaging and materials should be stored and taken to a recycling centre so it can be disposed of in a manner which is compatible with the environment.
  8. The following symbol means that you should 'Reduce – Reuse – Recycle'.
- 
9. We are a Member of the VALPAK National Compliance Scheme and our registration number is **RM08660**.
  10. For further information about disposal please contact your Local Authority.
  11. You can also get more advice and guidance about recycling at the following website  
<http://www.recycle-more.co.uk>
  12. Should you pass this product on to another user either sold or loaned, you **MUST** pass on this user manual.  
This will make sure that all other users can use and maintain this machine safely.


# Declaration of Conformity

Genpower Ltd confirms that these PIPE products conform to the following CE directives.  
97/68/EC Non Road Mobile Machinery Directive  
2000/14/EC Outdoor Noise Directive  
2004/108/EC Electro Magnetic Compatibility Device  
2006/42/EC Machinery Directive

## EC DECLARATION of CONFORMITY

The undersigned, as authorised by: **GENPOWER Ltd**

Conforms to the Directive **2000/14/EC (as amended)** of the European Parliament and of the council on the approximation of the laws of the Member States relating to the noise emission in the environment by equipment for use outdoors.

Equipment category:	Power Equipment
Product Name/Model:	P10000LE
Type/ <u>Serial No</u> :	Open Frame Generator
Net installed power:	7.5kW
The technical documentation is kept by:	Roland Llewellyn, c/o Genpower Ltd, Isaac Way, Pembroke Dock, Pembrokeshire, SA72 4RW
The conformity assessment procedure followed was in accordance with annex <del>V</del> <u>VI</u> of the Directive.	
Notified Body:	AV Technology Ltd, Unit 12 Easter Court, Europa Boulevard, Warrington, Cheshire, WA5 7ZB
Certificate N <sup>o</sup> / <u>Test report N<sup>o</sup></u> :	OND-2016508-04-02 P10000LE
Measured Sound Power Level:	72dB
Guaranteed Sound Power Level:	72dB
A copy of this certificate has been submitted to the European Commission and to EU Member State United Kingdom.	
Place of Declaration:	Pembroke Dock, SA72 4RW
Date:	06 March 2018
Name:	Roland Llewellyn
Signature:	
Position in Company:	Managing Director
Name & address of manufacturer or Authorised representative	Genpower Ltd, Isaac Way, Pembroke Dock, Pembrokeshire, SA72 4RW



## Contact Details

Postal Address	Genpower Limited London Road, Pembroke Dock, Pembrokeshire. SA72 4RW. UK
Telephone	+44 (0) 1646 687880
Fax	+44 (0) 1646 686198
Website	<a href="http://www.p1pe.co.uk">www.p1pe.co.uk</a>

## Warranty

To register your machine for the manufacturer's warranty, please visit:

<http://www.p1pe.co.uk/warranty>







**P1PE – Position One Power Equipment**  
**Isaac Way, Pembroke Dock, Pembrokeshire,**  
**SA72 4RW. UK**

**[www.p1pe.co.uk](http://www.p1pe.co.uk)**