



Instruction manual

LED striplight

These instructions are for your safety. Please read through them thoroughly prior to use and retain them for future reference.

Parts and Fittings Supplied

Ref	Description	Illustration	Qty	Ref	Description	Illustration	Qty
A	Light fitting		1	C	Mounting Accessories		2
B	Connector		1				2
			1				

Tools Required (not supplied)

- 6mm Cross Headed Screwdriver
- Pencil

Safety and Maintenance Information

- Check the pack and make sure you have all of the parts listed.
- This product is suitable for indoor use only and not for areas constantly subject to moisture such as bathrooms and so on.
- Caution: Do not stare directly at the LED light beam.
- This product is suitable for installation on surfaces with normal flammability e.g. wood, masonry. It is not suitable for use on highly flammable surfaces or in flammable atmospheres.
- The product must be securely fixed to the mounting surface using the screws supplied. The screws supplied are suitable for "wooden board" only. Other fixings not supplied and must be purchased.
- Take care not to drill into any pipes or mains cables beneath the surface during mounting holes preparation.
- Never use the terminal cables to bear the product weight.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
- Ensure that the cables are fully unwound before use. Always organise cables and extension leads so that they will not present a hazard.
- Do not position this LED light where it may be covered by other items e.g. curtains, nets or bedding.
- To avoid electric shock, do not tamper with the on/off switch. If the switch becomes loose or damaged, the product should be destroyed.
- If the external flexible cable or cord of this luminaire is damaged, it must be replaced by a special cord or cord exclusively available from the manufacturer or his service agent.
- Always switch off or disconnect from the mains when cleaning the product.
- Wipe clean with a soft dry cloth. Never use scourers, abrasives or chemical cleaners. Do not allow moisture to come into contact with electric parts.
- All fitting must be installed by a competent person in accordance with local regulations

Specification

Art Nr.	Input:	Wattage:	Ra :	Color Temperature :	Total lumen:	Max. number of inter-connected
9478R	220~240 VAC	5 W	>80	4000 K	400 lm	20 pcs
4012R	220~240 VAC	9 W	>80	4000 K	700 lm	10 pcs
5766R	220~240 VAC	12 W	>80	4000 K	1000 lm	8 pcs
5137R	220~240 VAC	15 W	>80	4000 K	1250 lm	6 pcs
1069R	220~240 VAC	20 W	>80	4000 K	1650 lm	5 pcs

	Conformity with all relevant EC Directive requirements
	Class II product - Double Insulated - No earth required
	This product is not suitable for dimming
	Waste electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority or local store for recycling advice
	For indoor use only
xxWyy	Manufacturing date code xx: year of manufacturing; yy: week of manufacturing

