

Bulb

This product contains 11W LED module and is not replaceable.

Cleaning

We recommend cleaning with a soft dry cloth.

Do not use solvents or abrasive cleaners as these could damage the finish.

Glass parts – Wipe clean with a damp cloth. Do not use abrasive materials as these will damage the finish.

Recycling advice





Waste electrical products should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority or retailer for recycling advice. The packaging on this product can also be recycled.

Safety information

For your safety, always switch off the supply before changing lightbulbs, or cleaning.

The glass shade must be replaced if it becomes cracked or damaged.

Do not use product without glass shade attached.



Non-replaceable control gear



Non-replaceable light source

Instruction leaflet

Outdoor Rectangular Black Frame Lantern with Integrated Light

983PG



UK Manufacturer:

Kingfisher International Products Limited,
3 Sheldon Square, London, W2 6PX,
United Kingdom.

EU Manufacturer:

Kingfisher International Products B.V.
Rapenburgerstraat 175E,
1011 VM Amsterdam, The Netherlands.

14/05/2021



Thank you for purchasing this light fitting. Please read the instructions carefully before use to ensure safe and satisfactory operation of this product. Please retain these instructions for future reference.

Warning

This is a Class 1 product and must be earthed.

This product is only suitable for connection to a 240V~50Hz supply in accordance with current IEE wiring regulations. It should be installed in accordance with local building regulations.

This product is IP44 rated and is suitable for outdoor use.

Before installing your light fitting always switch off the mains supply and remove the appropriate fuse or switch off the appropriate circuit breaker before commencing installation.

This product contains glass so care must be taken when fitting or handling to prevent personal injury or damage to the product. If replacing an existing fitting, make a careful note of the connections.

This product is suitable for installation on surfaces with normal flammability e.g. wood, masonry. It is not suitable for use on highly flammable surfaces or in flammable atmospheres.

Never put anything on the product or hang anything on any part of this product.

This product contains non-replaceable LEDs.

If you are in any doubt about your competence please consult a qualified electrician.

If any modification is made it will invalidate the warranty and may render the product unsafe.

Keep children and animals away from the assembly area.

This fitting contains small parts that could cause choking if swallowed.

Keep all plastic wrapping materials away from children to avoid danger of suffocation.

Ensure that all packaging is disposed of carefully and responsibly.

Specification

Voltage:	240V 50Hz	IP rating:	44
Lamp:	Max. 1 x 11W LED module		

Kit Contents

- This kit contains:
- Light fitting
 - Fixing pack

Fixing Instructions


Make sure you have the following items which are required to install this light fitting:

- Selection of cross and flat head screwdrivers.
- Electric drill and assorted drill bits.
- Wire strippers.

Installation

Decide on the position of the light fitting, or remove existing light fitting. **Take a note of the position of the electrical connections.**

- Remove the two side screws (A). Retain them for refitting later. Use the fixing bracket (B) as a template, mark the screw holes, and secure to the wall with appropriate fixings (C), making sure the bracket is correctly aligned.
- Bring the mains cable through the rubber grommet. Open the terminal block box and connect the house wiring to the internal terminal block (D) – see expanded wiring details below. **NOTE: This is a Class 1 product and must be Earthed.** The cable entry grommet must be securely in place to ensure that the water ingress protection is maintained.

- Remember to close the terminal box cover once complete and make sure the earth cable is securely connected to the earth screw (E) marked .
- Secure the fitting over the bracket by using the screws (A) removed in Point 2.
- Turn on the power and test.

