



INSTALLATION & MAINTENANCE MANUAL

**CSP1xx / CSP2xx / CSP3xx / CSP4xx**

## GENERAL INSTRUCTIONS

**These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.**

**These instructions should be used to aid installation of the following products:  
CSP1xx / CSP2xx / CSP3xx / CSP4xx**

## SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this luminaire is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Please note the IP (Ingress Protection) rating of this product when deciding the location for installation
- This product is Class I and must be earthed
- This product is IP20 rated

## INSTALLATION

- Provide power to the required point of installation
- Remove the mounting bracket from the luminaire by removing the screws on the side
- Using the mounting bracket as a template, mark the location for, and drill the fixing holes ensuring not to infringe with any gas/water pipes or electrical cables. The CSP4xx has two brackets which must be mounted 360mm apart
- Fix the bracket using the screws provided
- Connect the luminaire to the mains supply ensuring the correct polarity is observed:  
L - Live (brown), E - Earth (green/yellow), N - Neutral (blue)
- Align the luminaire with the mounting bracket and refasten the screws
- Insert suitable GU10 lamps using the suction cup provided
- Switch on and check for correct operation

## GENERAL

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

This product is dimmable dependent on lamp type.

## WARRANTY

This product has a warranty of 1 year from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

**INTERNATIONAL  
CONTACT DETAILS**



230V  
50Hz



IP20



**ML**  
ACCESSORIES LTD



CE UK  
CA



101

**ML Accessories Limited LU5 4LT**  
**[www.mlaccessories.co.uk](http://www.mlaccessories.co.uk)**

DCJUL21\_V2