



LED BULKHEAD CEILING LIGHT

**PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE INSTALLATION
LEAVE A COPY FOR THE USER / MAINTENANCE ENGINEER FOR FUTURE REFERENCE**

IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out in accordance with the latest edition of the National Wiring Regulations, if in doubt consult a qualified electrician.
- All luminaires run hot. It is the installer's responsibility to consider fire risk and take appropriate precautions.
- Input voltage - 240V 50Hz AC.
- IP65 Rated suitable to resist low pressure jets of water.



This luminaire is not suitable for covering with insulation material.

INSTALLATION INSTRUCTIONS

Always isolate mains supply before servicing, fitting or moving position of the luminaire or changing the lamp

1. Select the required position for the luminaire and provide a suitable power supply to this point, taking into account the possible power entry points of the luminaire.
2. Remove the diffuser and trim from the body
3. Fix the base to the wall or ceiling as required. Beware of joists, water pipes and electric cables when applying the fixing screws.
4. Connect the mains supply to the bulkhead cable using a suitable junction block:
 - Switched Live (Brown)
 - Neutral (Blue)
 - Earth – (green/yellow) to terminal marked 
5. Refit the diffuser and trim
6. Switch on the power supply.

N.B. These luminaires must be earthed.

Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX(UK Only)



Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his takeback of the product for the correct disposal.

WARRANTY

See www.auroralighting.com for full details of warranties and Extended Warranty Terms and Conditions. The warranty is invalid in the case of improper use, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the warranty period it will be replaced free of charge, this is subject to correct installation and return of the faulty product. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.