



## AU-DL10013AW, AU-DL10019AW & AU-DL10032AW

**PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE INSTALLATION  
LEAVE A COPY FOR THE USER / MAINTENANCE ENGINEER FOR FUTURE REFERENCE**

### IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out in accordance with the latest edition of the National Wiring Regulations. If in doubt, consult a qualified electrician.
- Mains supply voltage 220-240V AC, 50/60Hz
- Dimmable.
- These luminaires are for indoor use only.
- There are no replaceable parts in this luminaire
- This luminaire is IP44 rated and is suitable for bathroom zones 1 and 2.



This luminaire is not suitable for covering with insulation material.

### INSTALLATION INSTRUCTIONS

Before commencing installation or maintenance, ensure electricity is switched off at the mains.

1. Select the required position for the luminaire ensuring there is a 50mm clearance around the luminaire. Beware of joists, water pipes and electric cables.
2. Cut-out sizes:
  - AU-DL10013AW = 90mm
  - AU-DL10019AW = 150mm
  - AU-DL10032AW = 210mm
3. Connect the mains supply to the LED driver:  
Brown – Live, Blue – Neutral
4. Plug the LED driver into the downlight
5. Push the LED driver into the ceiling and away from the downlight
6. Slide the legs of the mounting spring clips into the ceiling cut-out and push the luminaire up into the aperture. Ensure that it is securely located.
7. Switch on the power supply.

### Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX (UK Only)



Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his takeback of the product for the correct disposal.

### Warranty

See [www.auroralighting.com](http://www.auroralighting.com) for full details of warranties and Extended Warranty Terms and Conditions. The warranty is invalid in the case of improper use, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the warranty period it will be replaced free of charge, this is subject to correct installation and return of the faulty product. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.