



LED FLAT PANELS

**PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE INSTALLATION
LEAVE A COPY FOR THE USER / MAINTENANCE ENGINEER FOR FUTURE REFERENCE**

IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out in accordance with the latest edition of the National wiring regulations. If in doubt please consult a qualified electrician.
- Input voltage – 220-240V 50Hz AC
- These luminaires are for indoor use only.
- These luminaires are not dimmable.
- The AU-FP600A is suitable for installation into 600mm grid ceilings and installation in European T-bar ceilings (15 & 24mm)
- Nominal dimensions: 595 x 595 x 8mm
- The luminaire must not under any circumstances be covered with any insulation materials
- Insure that ALL electrical connections are tight with no loose strands.



This luminaire is not suitable for covering with insulation material.

INSTALLATION INSTRUCTIONS

Isolate the mains supply before servicing or installation

1. Remove the selected 600 x 600mm ceiling panel and an adjacent panel to allow for installation of the LED Panel and LED Driver
2. Connect the mains supply to the LED Driver supplied with the panel:
 - Brown – L (Live)
 - Blue – N (Neutral)
 - Green/Yellow – ⊕ (Earth)
3. Plug the lead from the driver into the LED panel Jack plug
4. Replace the adjacent ceiling panel
5. Switch on the supply.

Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX (UK only)



Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his take back of the product for the correct disposal.

Warranty

See www.auroralighting.com for full details of warranties and Extended Warranty Terms and Conditions. The warranty is invalid in the case of improper use, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the warranty period it will be replaced free of charge, this is subject to correct installation and return of the faulty product. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.