



MiHome™
your switch is mi command



This product requires the MiHome Gateway to function

MiHome Multiplug

The MiHome Multiplug is a 4-gang extension lead. It is a control only product. Each socket on the extension lead is individually controllable. This allows you to use all the control features in the MiHome App including simple on/off, timers and geofencing on each socket individually. The Multiplug is also controllable via the MiHome remote control (MIHO003).

This product only receives communications from the MiHome Gateway and does not send a response therefore it is not recommended for use in safety critical applications.

Technical information:

- Product code: ENERO10
- Radio Frequency: 433.92Mhz (ISIM band)
- Transmitter Output power: 3 V /+12 dBm /27 mA
- Range in open area: Ca. 25 metres
- Extension lead Rating: 220 - 250V- 50Hz, 13A, 3000W max.
- Socket Energy Efficiency: Consumes < 0.5W in Standby.
- Mains cable length: 1.8 Meter
- Number of sockets: 4
- Receiving Range: Typically 25 metres in open area
- Applications: Domestic appliances with a standard UK plug to BS1363.

ENERGENIE®
your switch is my command

0844 412 7923
energenie4u.co.uk

