



If this product fails through faulty materials or workmanship, contact our service department direct on: +44 (0) 1926 818186. Normal wear and tear are excluded as are consumable items and abuse.

## www.power-tec.co.uk



Kineton Road, Southam, Warwickshire CV47 0DR T+44 (0) 1926 815000 F+44 (0) 1926 815888





www.power-tec.co.uk





# POWER C

## **Hot Stapler Plastic Repair System**

- Professional





- 1. Plug in to standard 240v system.
- 2. Press On/Off button to switch on.
- Set the temperature control knob to:
  L for thin plastic (bumpers etc).

M for 5mm thick plastic (spot lights etc).

H for thick or hard plastic.

- 4. Choose suitable staple for repair and insert it into the tips.
- 5. Prepare plastic for repair by butting together.
- 6. Heat staple by pressing and holding the handle switch for 10 seconds.
- 7. Press the pin gently against the plastic to be repaired; push staple until it about half way through material, then twist through about 10° to 15°.
- 8. Release the heat button and hold the staple on the repair until it feels firm.
- 9. Slowly withdraw the tool, leaving the head of the staple in place.
- 10. Cut off the protruding ends of the staple.
- 11. Remove the remaining ends of the staple with sander.
- 12. Continue with repair in the normal way.

When repairing large areas, repeat the procedure at regular intervals. 300 x Stainless Steel staples supplied - (replacements available).

2-pin plug included.

Note:

Staple Description	Size	Part No
V shaped (supplied)	0.6mm x 100pcs	92260
U shaped (supplied)	0.6mm x 100pcs	91782
U shaped (supplied)	0.8mm x 100pcs	91783



Safety First. Be Protected.

#### Caution

### Always wear safety goggles when cutting staples

- Once the pin is in the stapler and the heat is applied, the staple will become extremely hot. (100-200°C). Do not touch without full protection.
- Do not use with wet hands.
- Do not soak product with water.
- Do not use in wet conditions.
- Turn off when unattended and make sure the tips are cold before leaving on any surface.
- Do not use for any purpose other than that it is intended for.
- Make sure all health and safety procedures are in place before commencing work.

The Tool Connection cannot be held responsible for any damage caused to property or personnel when using this product.

www.power-tec.co.uk

www.power-tec.co.uk



