

Technical Data

13 Amp Socket Outlet with USB Charger

Item No: 4087P

Brief product description:

Power and charge your MP3 player, mobile phone, tablet, camera or any other USB chargeable or powered device.

Features:

- 3.1A total output, shared across 2 outlets
- Colour coded terminals with backed out captive screws for easy installation
- Twin earth fitted as standard
- Ideal for retrofit, fits 25mm box
- USB charger stand-by power made when not in use
- 2 x Type A, 5V USB sockets
- With smart USB connectivity
- Standby mode when device is fully charged
- Auto detects USB device & adjusts charging pattern to suit

Product images:



Technical Specifications:

Standard(s)	BS 5733 BSEN 60950	 
ASTA Approved	License no.1182	
Rating	13 Amp 240V~	
Contact Gap	3.0mm minimum	
Switch type	Single pole	
Terminal Capacity - L & N	3 x 2.5mm ² 3 x 4mm ² 2 x 6.0mm ²	
RoHS Directive	No	
WEEE Directive	No	
Mounting Box Depth (Min)	25mm	
Fixing Centres	120.6mm	
Size	146.5mm x 86mm x 35mm	
USB Output	5V $\overline{\text{---}}$ 3.1A (output shared across two ports)	
Output Tolerance	<5%	
Stand-by Power	<75mW	

UK LAP Technical Helpline 0800 068 0292

Powersmith Ltd, BA22 8RT